




Inductive sensor

NJ4-12GM50-WS-20M

- 20 m cable length



Dimensions



Technical Data

General specifications		
Switching function		Normally open (NO)
Output type		Two-wire
Rated operating distance	s _n	4 mm
Installation		non-flush
Output polarity		AC
Assured operating distance	s _a	0 ... 3.24 mm
Reduction factor r _{Al}		0.4
Reduction factor r _{Cu}		0.4
Reduction factor r ₃₀₄		0.7
Nominal ratings		
Operating voltage	U _B	20 ... 253 V
Switching frequency	f	0 ... 20 Hz

Refer to "General Notes Relating to Pepperl+Fuchs Product Information".

Pepperl+Fuchs Group
www.pepperl-fuchs.com

USA: +1 330 486 0001
fa-info@us.pepperl-fuchs.com

Germany: +49 621 776 1111
fa-info@de.pepperl-fuchs.com


Singapore: +65 6779 9091
fa-info@sg.pepperl-fuchs.com

 **PEPPERL+FUCHS**

Technical Data

Voltage drop	U _d	typ. 4 V at 15 ... 200 mA typ. 6.5 V at 5 mA
Momentary current (20 ms, 0.1 Hz)		0 ... 1200 mA
Operating current	I _L	5 ... 200 mA
Off-state current	I _r	typ. 0.7 mA
Time delay before availability	t _v	≤ 30 ms
Switching state indicator		LED, yellow
Compliance with standards and directives		
Standard conformity		
Standards		EN 60947-5-2:2007 IEC 60947-5-2:2007
Approvals and certificates		
UL approval		cULus Listed, General Purpose
CSA approval		cCSAus Listed, General Purpose
Ambient conditions		
Ambient temperature		-25 ... 70 °C (-13 ... 158 °F)
Mechanical specifications		
Connection type		cablc PVC , 20 m
Core cross-section		0.34 mm ²
Housing material		Stainless steel 1.4305 / AISI 303
Sensing face		PBT
Degree of protection		IP67
Note		1) In the temperature range below 0 °C, permissible operating voltage U _b 80...253 V Safety fuse ≤ 0.8 A (quick-blow) according to IEC 60127-2 Sheet 1 Recommendation: after a short circuit, check that the device is functioning correctly.

Connection



Accessories

	BF 12	Mounting flange, 12 mm
---	--------------	------------------------

Release date: 2020-03-20 Date of issue: 2020-03-30 Filename: 118786_eng.pdf